

DATASHEET

Double Touch Panel and Scene Controller

HSC-S514

Z-Wave 800 Series in-wall touch panel with two relay channels and four scene keys. Control two lighting circuits and start up to four scenes from one glass panel.

Rev. 1.0 | October 2026



Key features

- Two relay channels for direct load control. Four additional scene keys.
- Scene keys send Central Scene and Scene Activation commands for short and long press.
- Tempered safety glass panel with an LED indicator on each key.
- Z-Wave 800 Series radio. Acts as a repeater in the Z-Wave mesh network.
- Direct association: each key can control up to 5 Z-Wave devices.
- Configurable beeper, LED brightness, key modes, and auto-off timers.

Applications

- **Hotels:** guest-room automation tied to occupancy and check-in status.
- **Short-term rentals:** remote control and scheduling between stays.
- **Schools:** classroom automation that cuts energy use in empty rooms.
- **Light commercial:** offices and retail spaces with scheduled operation.

Key specifications

Model	HSC-S514
Keys	6 (2 relay keys, 4 scene keys)
Power supply	90 to 250 VAC, 50/60 Hz. Neutral wire required
Maximum load	2 x 3.5 A resistive, 2 x 2 A capacitive/inductive (per channel)
Wireless protocol	Z-Wave 800 Series, 908.42 MHz (US)
Finish	White tempered glass
Use	Indoor only

Compliance

Safety listing	Covered by ETL listing control no. 4010498
-----------------------	--

Radio	FCC Part 15. FCC ID: [TBC: confirm FCC ID on product label]
Z-Wave certification	[TBC: Z-Wave Alliance certification in process. Add certificate number when issued]

Ordering information

SKU	Description
HSC-S514	Double touch panel and scene controller, Z-Wave 800 Series, white glass

Specifications can change without notice. For installation, configuration, and safety information, read the user manual.