

NUVO

200 Watt Rack-Mount Subwoofer Amplifier

Delivering a stand-out bass response, the NV-SUBAMP200-xx subwoofer amplifier offers maximum versatility and rack-mount capability. The amplifier and optional NV-SUBIW8 passive in-wall subwoofer are designed to integrate with almost any audio system.



- **Powerful all digital subwoofer amplifier ideal for medium sized audio installations**
- **Installation-friendly rack-mountable design**
- **Unfiltered LFE (low frequency effects) and RCA line level inputs**
- **EQ settings for use with any Nuvo passive in-ceiling or in-wall subwoofers**
- **Signal-sensing power ON/OFF**
- **Variable crossover and phase adjustment**
- **Two year warranty**
- **Efficient all-digital 200 watt amplifier**
- **12V DC trigger inputs and outputs**

The NV-SUBAMP200-xx features signal-sensing power activation (optional setting) to automatically turn on when it detects a signal from the receiver. It will return to standby automatically after approximately 15 minutes of no signal. Unfiltered LFE / RCA stereo inputs let you easily connect the amplifier to most modern receivers. The variable crossover and phase controls allow you to match the Subwoofer output with the main speakers for premium performance and sound. 12V DC input and output triggers allow external devices to control the amplifier or for it to control external items. A three-position EQ switch allows the amplifier output to be tailored to any Nuvo in-ceiling or in-wall passive subwoofers.

One or two NV-SUBIW8 subwoofers may be used with one NV-SUBAMP200-xx. The optional NV-SUBIW8 adds a powerful low-frequency impact to smaller home theater or audio installations. It is a sealed design to allow discreet mounting choices. A square magnetic grill is included.



Nuvo 200 Watt Rack-Mount Subwoofer Amplifier

Material	Stamped Steel Rack Mount Enclosure	Line Output Connector	RCA Analog (L/R)
Color	Black	Trigger Input	2.0V - 20V (12V Recommended)
Unit Size without Feet (mm)	482.6 x 226.8 x 43.2	Trigger Output	2.0V - 20V (12V Recommended)
(in)	19 x 8.9 x 1.7	Input Voltage	110-120VAC / 220-240VAC Manual Switch
Unit Size with Feet (mm)	482.6 x 226.8 x 49.2	Speaker Output	Dual 5-Way Binding Posts (Outputs in Parallel)
(in)	19 x 8.9 x 1.9	Output Power	200W @ 4 Ohm 100W @ 8 Ohm
Unit Weight (kg)	2.72	Frequency	20-200 Hz
(lbs)	6	Distortion	<1% THD +N 20-200Hz
Shipping		Speaker Impedance	8 Ohm / 4 Ohm
Package Dimensions (mm)	539 x 281 x 147.5	Signal-to-Noise Ratio	>86dB
Package Dimensions (in)	21.2 x 11.1 x 5.8	Line Input Impedance	15k Ohm
Package Shipping Weight (kg)	3.1	Regulatory Approvals	cTUVus, CE-LVD, UL62368, CB IEC62368, SAA (Aus/NZ), RCM (Aus/NZ) FCC Part 15 (B, C)
Package Shipping Weight (lbs)	6.83		CE (EMD/LVD) EN55032, EN55020, EN61000-3, EN61000-3-3, EN62368 RoHS (Restriction of Hazardous Substances Directive 2002/95/EC)
Humidity	70% non-condensing		Legrand reserves the right to change specifications without notice.
Interoperability	Use up to two NV-SUBIW8 Subwoofers		
Mounting	Standalone or 1U Rack Mount		
Line Input Connector	RCA Analog (L/R)		
High Level Input Connector	4-pin Phoenix Connector (Stereo +/-)		

designed to be better™



Legrand, North America

3015 Kustom Drive
Hebron, KY 41048
United States
844.334.8044
www.legrand.us/nuvo