

## 2-Channel RF Transmitters & Receiver

### SK-919TD2A-UP

*Fixed-Code RF Transmitter*

### SK-917T2A-U

*CODEBUMP™ Transmitter*

- ▶ Operates up to 500ft, 315MHz
- ▶ LED transmission indicator
- ▶ Includes 12VDC alkaline battery
- ▶ Compatible with all SECO-LARM receivers
- ▶ SK-919TD2A-UP: 68 billion possible codes
- ▶ SK-917T2A-U: 18 quintillion possible codes



2 1/4" x 1 1/4" x 1 1/2"  
(83x85x28 mm)

### SK-919TP2H-NU

*Handheld Transmitter*

- ▶ Operates up to 500ft, 315MHz
- ▶ Over 68 billion (6.8x10<sup>10</sup>) possible codes
- ▶ Includes two 3VDC lithium batteries
- ▶ Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SL-SK9HBC)
- ▶ Slimline design



3 1/2" x 2 3/16" x 1/2"  
(89x56x12 mm)

### SK-910RB2Q

*Two-Channel Receiver*

- ▶ 5 Programmable relay output modes:
  - 4-Second Momentary Output
  - 1-Second Momentary Output
  - Latch Output
  - Validity Output
  - Toggle Output
- ▶ Flexible operating voltage: 11~24 VAC/VDC
- ▶ Up to 500ft (152m) range
- ▶ Independently programmable channels with 5 output modes
- ▶ Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- ▶ Compatible with all SECO-LARM transmitters (fixed code and CODEBUMP™)
- ▶ 2 LEDs indicate RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode

**Now Available!**

Independently programmable channels with 5 output modes



3 1/4" x 3 3/8" x 1 1/8"  
(83x85x28 mm)

### SK-910RB2Q Specifications:

Operating frequency	315MHz	
Memory capacity	15 transmitter button codes per channel, 30 per receiver	
Operating voltage	11~24 VAC/VDC	
Operating current	Standby	8mA@12VDC
	Active	30mA@12VDC per channel
Relay output modes	4-sec. momentary, toggle, latch, validity, 1-sec. momentary	
Relay contact rating	Form C 10A@24VDC or 120VAC per channel	
Connectors	Screw terminals, +, -, NO/NC/COM per channel	
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)	

**SECO-LARM®**

16842 Millikan Avenue  
Irvine, CA 92606

Tel: 1-949-261-2999

1-800-662-0800

Fax: 1-949-261-7326

Web: [www.seco-larm.com](http://www.seco-larm.com)

Email: [info@seco-larm.com](mailto:info@seco-larm.com)



Copyright © 2010  
SECO-LARM U.S.A., Inc.  
All rights reserved