

ASI

Streamer

Features

- Connect to any commercial or residential amplifier as a digital streaming source
- Link up to 12 a-live units in a single installation
- Stream same or different music from popular services to all zones
- Also stream from RCA/USB inputs or files on mobile device
- ESS Sabre HiFi DAC
- RCA/Coax/Optical outputs
- Set your favorite playlist music as an alarm clock
- LAN connection for streaming in WiFi saturated areas
- Decoding up to 24 bit, 192KHz



Specifications

Connectivity	Wireless Network	IEEE802.11 b/g/n 2.4G
	LAN	single 10/100M RJ45
Frequency Response		20Hz to 20KHz
Power Input		DC 12V, 1A
Audio Source Input		USB 2.0, Analog RCA
Audio Source Output		Analog RCA, Coaxial, Optical(2.1)
Dimensions		3.9" (L) x 4.1" (W) x 1.1" (H)
Weight		0.4 lbs
Music Format		MP3/AAC/AAC+/ALAC/APE/WAV
Decoding		Up to 24 bit/192KHz

Download the a-live™ app:



Optional Accessories



PVL30A
30W
P.A. Amplifier



PL200M
160W Four Zone
Commercial
Amplifier



PBM120A
120W
P.A. Amplifier